


FM/DAB+ TUNER

T11



DAB+ tuning



RDS (Radio Data System) capability for FM broadcasts



Includes remote control

Rotel has been producing quality tuners since the 1960s. One of the latest additions to this long-established line-up is the T11 FM/DAB+ tuner. It provides a wealth of listening options with easy access to classic analogue FM stations as well as newer DAB+ (Digital Audio Broadcasting) services. Like the

T14, T11 features the ability to easily store and recall up to 30 presets each for FM or DAB+ stations. A further useful feature common to all 14 Series products is the ability to dim the display panel and power LED to provide a comfortable visual reference in all lighting environments.

Rotel tuners provide a wealth of high quality listening choices. See more at

rotel.com



FM/DAB+ TUNER

T11



SPECIFICATIONS

FM Tuner

Usable Sensitivity	22.2 dBf
50dB Quieting Sensitivity	27.2 dBf (mono)
Signal to Noise Ratio	
Mono	63 dBf (at 65 dBf)
Stereo	60 dBf (at 65 dBf)
Harmonic Distortion	
Mono	0.2% (at 65 dBf)
Stereo	0.3% (at 65 dBf)
Frequency Response	10Hz - 15kHz, \pm 3dB
Stereo Separation (100Hz/1kHz)	40 dB / 37 dB
Analog Output	1.0 V
Antenna Input	75 Ohms F connector

DAB Tuner

Sensitivity	-80 dBm
Tuning Range	Band III (174 - 240MHz)
Audio Data Rate	224kbps (Max)
Frequency Response	20 - 20kHz, \pm 1.0 dB
Analog Output	2.1V at 0 dBFS
Antenna Input	75 Ohms F connector

General

Power Requirements (AC)	
Europe	230V, 50Hz
USA	120V, 60Hz
Power Consumption	10 watts
Standby Power Consumption	< 0.5 watts
Finishes	Silver and Black
Dimensions (W x H x D)	430 x 73 x 331mm 17" x 2 7/8" x 13"
Front Panel Height	60mm, 2 3/8"
Weight (net)	4.3 kg, 9.5 lb

Rotel tuners provide a wealth of high quality listening choices.

See more at

rotel.com

