

Audio

Frequency response 55Hz – 20kHz

Driver 75mm Ruark NS+

Amplifier 9W

Enhancements Adjustable EQ, loudness

Cabinet type Tuned reflex enclosure

Connectivity

Digital radio DAB / DAB+

Multiregional FM World, USA, Japan, Korea

Bluetooth V4.2 SBC, AAC, BLE, A2DP

Line-in 3.5mm stereo jack (1.4Vrms max)

Headphone 3.5mm jack, 25mW into 16-32 Ohm

USB 2.0, (5V 1A) MP3, AAC up to 48kHz 320kbps,

FLAC up to 24-bit 96kHz, WAV up to 24-bit 96kHz,

WMA up to 44.1kHz 320kbps

External telescopic aerial 75Ω F-type connector

Features

Display High-contrast OLED with auto dimming

Dual alarms Daily, custom, weekends, weekdays

Auto-standby Automatic power saving mode

DST Configurable daylight-saving settings

Real time clock with internal battery backup

Security slot Kensington compatible

User interface languages:

EN, DA, DE, ES, FR, IT, JA, KO, NL, NO, PL, RU, ZH

General Specifications

Finishes Espresso, Light Cream

Box contains R1, AC power adapter, quick start guide

Power adapter 100-240VAC, 50-60Hz input, 14VDC

1.5A output, 1.8m cable, 2.1 × 5.5mm DC plug

Power consumption 0.7W standby, 4-8W typical

Product dimensions H175 x W130 x D135mm

Product weight 1.4kg

Packaged weight 2.0kg

Inner carton dimensions W180 × H270 × D210mm

Outer carton dimensions W559 × H295 × D427mm

Outer carton 6 pcs / 13.5kg

Espresso product code/EAN


R1D-ESP / 5060637250075

Rich cream product code/EAN

R1D-LCR / 5060637250082

Optional accessories

BackPack battery pack



Remote

